

PLC-XF1000 IR Command List

- Transmission format of LCD projector operation key
: NEC Format (single command / command pipelining mode)
- Custom Code + Custom Code
: 8 patterns as below
33h+00h(Default; code1),33h+11h(code2),33h+22h(code3),33h+33h(code4),
33h+44h(code5),33h+55h(code6),33h+66h(code7),33h+77h(code8)

| Key No. | Data Code (HEX) | Function |
|---------|-----------------|--------------|
| 1 | -- | LIGHT |
| 2 | 00 | ON-OFF |
| 3 | 1C | MENU |
| 4 | 89 | AUTO PC |
| 5 | 8B | SHUTTER |
| 6 | 8C | CURSOR UP |
| 7 | 1E | CURSOR LEFT |
| 8 | 0F | SELECT |
| 9 | 1D | CURSOR RIGHT |
| 10 | 8D | CURSOR DOWN |
| 11 | 40 | LENS SHIFT |
| 12 | 82 | SCREEN |
| 13 | 0C | IMAGE ADJUST |
| 14 | 47 | ZOOM + |
| 15 | 4A | FOCUS + |
| 16 | 38 | INPUT 1 |
| 17 | 46 | ZOOM - |
| 18 | 4B | FOCUS - |
| 19 | 39 | INPUT 2 |
| 20 | 43 | FREEZE |
| 21 | 88 | D. ZOOM |
| 22 | 06 | INPUT 3 |
| 23 | 8A | P-TIMER |
| 24 | 5B | KEYSTONE |
| 25 | 08 | INPUT 4 |
| 26 | 1A | FILTER |
| 27 | 0D | IMAGE SELECT |
| 28 | 16 | INFORMATION |